



1.2 GHz to 1.6 GHz

Model No.	Frequency 1 GHz	Frequency 2 GHz	Gain dB (Min/Typ)	Flatness dB (Max/Typ)	Noise dB (Max/Typ)	P-1dB dBm (Min/Typ)	IP3 dBm (Typ)	VSWR Input (Max/Typ)	VSWR Output (Max/Typ)	+12 /+15 VDC Current (mA) Nom/Max	Size
CA12-2201	1.2	1.6	22	±0.5	1.4	10	20	2.0:1/1.5:1	2.0:1/1.5:1	70	LCFB1
CA12-2202	1.2	1.6	22	±0.5	1.2	10	20	2.0:1/1.5:1	2.0:1/1.5:1	70	LCFB1
CA12-2203	1.2	1.6	22	±0.5	1.0	10	20	2.0:1/1.5:1	2.0:1/1.5:1	70	LCFB1
CA12-2204	1.2	1.6	22	±0.5	0.9	10	20	2.0:1/1.5:1	2.0:1/1.5:1	70	LCFB1
CA12-2208	1.2	1.6	20	±0.5	1.5	17	27	2.0:1/1.5:1	2.0:1/1.5:1	130	LCFB1
CA12-2209	1.2	1.6	20	±0.5	1.5	20	30	2.0:1/1.5:1	2.0:1/1.5:1	180	LCFB1
CA12-2210	1.2	1.6	20	±0.5	2.0	23	33	2.0:1/1.5:1	2.0:1/1.5:1	230	LCFB1
CA12-2211	1.2	1.6	20	±0.75	2.5	27	35	2.0:1/1.5:1	2.0:1/1.5:1	450	LCFB1
CA12-2212	1.2	1.6	20	±0.75	2.8	30	38	2.0:1/1.5:1	2.0:1/1.5:1	600	LCFB1
CA12-3201	1.2	1.6	32	±0.5	1.4	10	20	2.0:1/1.5:1	2.0:1/1.5:1	100	FB2
CA12-3202	1.2	1.6	32	±0.5	1.2	10	20	2.0:1/1.5:1	2.0:1/1.5:1	100	FB2
CA12-3203	1.2	1.6	32	±0.5	1.0	10	20	2.0:1/1.5:1	2.0:1/1.5:1	100	FB2
CA12-3204	1.2	1.6	32	±0.5	0.9	10	20	2.0:1/1.5:1	2.0:1/1.5:1	100	FB2
CA12-3208	1.2	1.6	30	±0.5	1.5	17	27	2.0:1/1.5:1	2.0:1/1.5:1	180	FB2
CA12-3209	1.2	1.6	30	±0.5	1.5	20	30	2.0:1/1.5:1	2.0:1/1.5:1	230	FB2
CA12-3210	1.2	1.6	30	±0.5	2.0	23	33	2.0:1/1.5:1	2.0:1/1.5:1	280	FB2
CA12-3211	1.2	1.6	30	±0.75	2.5	27	35	2.0:1/1.5:1	2.0:1/1.5:1	500	FB2
CA12-3212	1.2	1.6	30	±0.75	2.8	30	38	2.0:1/1.5:1	2.0:1/1.5:1	650	FB2
CA12-4201	1.2	1.6	42	±0.5	1.4	10	20	2.0:1/1.5:1	2.0:1/1.5:1	130	FB2
CA12-4202	1.2	1.6	42	±0.5	1.2	10	20	2.0:1/1.5:1	2.0:1/1.5:1	130	FB2
CA12-4203	1.2	1.6	42	±0.5	1.0	10	20	2.0:1/1.5:1	2.0:1/1.5:1	130	FB2
CA12-4204	1.2	1.6	42	±0.5	0.9	10	20	2.0:1/1.5:1	2.0:1/1.5:1	130	FB2
CA12-4208	1.2	1.6	40	±0.5	1.5	17	27	2.0:1/1.5:1	2.0:1/1.5:1	230	FB2
CA12-4209	1.2	1.6	40	±0.5	1.5	20	30	2.0:1/1.5:1	2.0:1/1.5:1	280	FB2
CA12-4210	1.2	1.6	40	±0.5	2.0	23	33	2.0:1/1.5:1	2.0:1/1.5:1	330	FB2
CA12-4211	1.2	1.6	40	±0.75	2.5	27	35	2.0:1/1.5:1	2.0:1/1.5:1	600	FB2
CA12-4212	1.2	1.6	40	±0.75	2.8	30	38	2.0:1/1.5:1	2.0:1/1.5:1	750	FB2

Ciao Wireless, Inc.

4000 Via Pescador / Camarillo / CA 93012

Tel (805) 389-3224 / Fax (805) 389-3629 / ciaowireless.com



1.2 GHz to 1.6 GHz

Ciao Wireless, Inc.

4000 Via Pescador / Camarillo / CA 93012

Tel (805) 389-3224 / Fax (805) 389-3629 / ciaowireless.com