



1.7 GHz to 1.9 GHz

Model No.	Frequency 1 GHz	Frequency 2 GHz	Gain dB (Min/Typ)	Flatness dB (Max/Typ)	Noise dB (Max/Typ)	P-1dB dBm (Min/Typ)	IP3 dBm (Typ)	VSWR Input (Max/Typ)	VSWR Output (Max/Typ)	+12 /+15 VDC Current (mA) Nom/Max	Size
CA12-2060	1.7	1.9	24	±0.5	1.2	10	20	2.0:1/1.5:1	2.0:1/1.5:1	70	LCFB1
CA12-2061	1.7	1.9	24	±0.5	1.0	10	20	2.0:1/1.5:1	2.0:1/1.5:1	70	LCFB1
CA12-2062	1.7	1.9	24	±0.5	0.8	10	20	2.0:1/1.5:1	2.0:1/1.5:1	70	LCFB1
CA12-2063	1.7	1.9	24	±0.5	0.7	10	20	2.0:1/1.5:1	2.0:1/1.5:1	70	LCFB1
CA12-2066	1.7	1.9	24	±0.5	1.2	13	23	2.0:1/1.5:1	2.0:1/1.5:1	70	LCFB1
CA12-2067	1.7	1.9	24	±0.5	1.2	15	25	2.0:1/1.5:1	2.0:1/1.5:1	100	LCFB1
CA12-2068	1.7	1.9	23	±0.5	1.2	17	27	2.0:1/1.5:1	2.0:1/1.5:1	120	LCFB1
CA12-2069	1.7	1.9	23	±0.5	1.4	20	30	2.0:1/1.5:1	2.0:1/1.5:1	150	LCFB1
CA12-2070	1.7	1.9	23	±0.5	1.5	23	33	2.0:1/1.5:1	2.0:1/1.5:1	200	LCFB1
CA12-2071	1.7	1.9	22	±0.5	1.8	27	35	2.0:1/1.5:1	2.0:1/1.5:1	450	LCFB1
CA12-2072	1.7	1.9	22	±0.5	2.0	30	38	2.0:1/1.5:1	2.0:1/1.5:1	650	LCFB1
CA12-3060	1.7	1.9	32	±0.5	1.2	10	20	2.0:1/1.5:1	2.0:1/1.5:1	100	FB2
CA12-3061	1.7	1.9	32	±0.5	1.0	10	20	2.0:1/1.5:1	2.0:1/1.5:1	100	FB2
CA12-3062	1.7	1.9	32	±0.5	0.8	10	20	2.0:1/1.5:1	2.0:1/1.5:1	100	FB2
CA12-3063	1.7	1.9	32	±0.5	0.7	10	20	2.0:1/1.5:1	2.0:1/1.5:1	100	FB2
CA12-3066	1.7	1.9	32	±0.5	1.2	13	23	2.0:1/1.5:1	2.0:1/1.5:1	100	FB2
CA12-3067	1.7	1.9	32	±0.5	1.2	15	25	2.0:1/1.5:1	2.0:1/1.5:1	140	FB2
CA12-3068	1.7	1.9	32	±0.5	1.2	17	27	2.0:1/1.5:1	2.0:1/1.5:1	170	FB2
CA12-3069	1.7	1.9	31	±0.5	1.4	20	30	2.0:1/1.5:1	2.0:1/1.5:1	200	FB2
CA12-3070	1.7	1.9	31	±0.5	1.5	23	33	2.0:1/1.5:1	2.0:1/1.5:1	250	FB2
CA12-3071	1.7	1.9	30	±0.5	1.8	27	35	2.0:1/1.5:1	2.0:1/1.5:1	500	FB2
CA12-3072	1.7	1.9	30	±0.5	2.0	30	38	2.0:1/1.5:1	2.0:1/1.5:1	750	FB2

Ciao Wireless, Inc.

4000 Via Pescador / Camarillo / CA 93012

Tel (805) 389-3224 / Fax (805) 389-3629 / ciaowireless.com